

# BIOS Release Notes

## TITLE

**SUBJECT:** MW83-RP0 BIOS Release Notes version [R09](#)  
**System:** [MW83-RP0-000](#)

### About This Release

**Build Date:** [2025/04/08](#)  
**BIOS Checksum:** [0xBE3F0F5F](#) (16M), [0x9AA4A3C6](#) (64M)  
**Release Owner:** ant.wei

### BIOS Components/Contents

**Processor stepping(s) supported:** IntelR Sapphire Rapids-WS/IntelR Sapphire Rapids-Refresh

**System hardware configurations supported:** MW83-RP0

**Microcode updates versions:**

CPUID	Family	Microcode Update ID
806f8	Sapphire Rapids/Sapphire Rapids Refresh E*/S*	2b000639

**IPMI support:**

**AMI Kernel version:** [Gbt\\_Kernel\\_037\\_01](#)

**Intel CSI/MRC Package version:** [0060.D53](#)

**SPI Descriptor version:** [16.11.20.1870v2](#)

**OPROM version :**

OPROM	Version
INTEL 10G PXE	2.3.24
AST2600 VGA	1.12.00
INTEL RAID PACKAGE	RSTe 8.6.0.1136

### Installation Notes

#### IMPORTANT NOTES:

1. Please extract the MW83-RP0\_[R09](#).zip to a bootable diskette that use FAT/FAT32 format

#### BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

#### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.

## BIOS Release Notes

Or

Enter \Tool\Win64 and execute f.bat for Windows 64bit.

4. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

## Known Issues/Workarounds

## Issues fixed in this version

R09

1. [Feature] Update RC 0060.D53 (Rev:3 2025.2 IPU Update Guidance (XLS) Reference Number: (KIT: 837181))
2. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b000639.pdb
3. [Bug Fix] Include INTEL-SA-01244 for CVE-2025-20054
4. [Bug Fix] Include INTEL-SA-01247 for CVE-2024-45332
5. [Bug Fix] Include INTEL-SA-01249 for CVE-2025-20109
6. [Bug Fix] Include AMI SA50292 for CVE-2023-6237, CVE-2024-5535, CVE-2024-6119
7. [Bug Fix] Include AMI SA50288 for CVE-2023-52353, CVE-2024-9143
8. [Bug Fix] Include AMI SA50290 for CVE-2024-38796

R08

1. [Feature] Improve KCS protocol
2. [Feature] Support Microsoft Option ROM UEFI CA 2023.
3. [Feature] Fine tune Setup Menu.

R07

1. [Feature] Update RC 0059.D28 (Fishhawk Falls SPR-R Maintenance Release6 BKC WW40'24 (KIT: 830802))
2. [Feature] Update CSME Firmware : 16.11.20.1870v2 (B1 Corporate)
3. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b000620.pdb

R06

1. [Feature] Update RC 0058.D81 (Fishhawk Falls SPR-R Maintenance Release5 BKC WW30'24 (KIT: 828362))
2. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b000603.pdb

R05

1. [Feature] Update RC 0058.D54 (Fishhawk Falls SPR-R Maintenance Release4 BKC WW28'24 (KIT: 825720))
2. [Feature] Update CSME Firmware : 16.11.17.1871 (B1 Corporate)

## BIOS Release Notes

3. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b0005d2.pdb
  4. [Feature] Update VROC UEFI 8.6.0.1136
- 

### R04

1. [Feature] Update RC 0055.D09 (Fishhawk Falls SPR-R BKC WW05'24 (KIT: 814803)).
  2. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b000590.pdb.
- 

### R03

1. [Feature] Win11 x64 23H2 Support
- 

### R02

1. [Feature] Update RC 0054.D12 (Fishhawk Falls SPR-R BKC WW50'23 (KIT: 794891)).
  2. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b000580.pdb.
  3. [Feature] Update RSTe VROC driver to v8.5.0.1096.
  4. [Feature] Add AMI SA50216 solution for CVE-2023-39539 and CVE-2023-39538.
- 

### R01

1. [Feature] Update RC 0053.D07 (Fishhawk Falls SPR-R BKC WW44'23 (KIT: 791719)).
  2. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b000571.pdb.
  3. [Feature] Update CSME Firmware : 16.11.15.1736 (B1 Corporate).
  4. [Feature] Update VROC driver to v8.2.0.1132.
- 

### T02

1. [Feature] Support Resizable BAR
- 

### T01

1. [Feature] Update RC 5172.D06 (Fishhawk Falls SPR-R BETA BKC WW36'23 (KIT: 787201)).
  2. [Feature] Update CSME Firmware : 16.11.15.1698 (B1 Corporate)
  3. [Feature] Update Microcode E\*/S\*: m\_87\_806f8\_2b0004d0.pdb
-