

BIOS Release Notes

TITLE

SUBJECT: MZ93-FS1 BIOS Release Notes version R12_F24
System: MZ93-FS1-000,R183-Z93-AAD1-000,R183-Z93-AAV1-000,
R183-Z94-AAD1-000,R183-Z94-AAV1-000,R183-Z94-AAD2-000,
R183-Z94-AAV2-000,R183-Z95-AAD1-000,R183-Z95-AAV1-000,
R183-Z96-AAD1-000,R183-Z96-AAV1-000,R283-Z94-AAD1-000,
R283-Z94-AAV1-000,R283-Z94-AAD2-000,R283-Z94-AAV2-000,
R283-Z95-AAD1-000,R283-Z95-AAV1-000,R283-Z96-AAE1-000,
R283-Z96-AAJ1-000,R283-Z96-AAE2-000,R283-Z96-AAJ2-000,
R283-Z96-AAE3-000,R283-Z96-AAJ3-000,E283-Z91-AAD1-000,
E283-Z91-AAV1-000,R183-Z93-LAJ1-000,R283-Z98-AAL1-000

About This Release

Build Date: 2025/03/21
BIOS Checksum: 0x7107F911 (32M)
Release Owner: Hex.Jan

BIOS Components/Contents

Processor stepping(s) supported: AMD Turin / Genoa Processors
System hardware configurations supported: MZ93-FS1-000
PCB Version: 1.x,3.x
Microcode updates versions:

| CPUID | Family | Microcode Update ID |
|----------------|--------------------------|---------------------|
| Turin A0 | Family 1Ah Model 00h-0Fh | 0x0B00004D |
| Turin B0 | Family 1Ah Model 00h-0Fh | 0x0B001016 |
| Turin C0 | Family 1Ah Model 00h-0Fh | 0x0B002032 |
| Turin C1 | Family 1Ah Model 00h-0Fh | 0x0B00211E |
| Turin Dense A0 | Family 1Ah Model 00h-0Fh | 0x0B10000F |
| Turin Dense B0 | Family 1Ah Model 00h-0Fh | 0x0B101028 |

IPMI support:
AMI Kernel version: 5.35_0ACST_PI1.0.0.3_017
AGESA PI version: TurinPI 1.0.0.3
OPROM version:

| OPROM | Version |
|---------|---------|
| AST2600 | 1.13.00 |

BIOS Release Notes

Installation Notes

IMPORTANT NOTES:

1. Please extract the MZ93-FS1_R12_F24.zip to a bootable diskette that use FAT/FAT32 format

BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Flash script for bios update:
 - 4.1 For AMD EPYC 9004 series CPU, execute f_GtoT.nsh
 - 4.2 For AMD EPYC 9005 series CPU, execute f.nsh
5. After bios flash finish, system must Power-Off to have the changes take effect.

BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. For AMD EPYC 9004 series CPU:
 - 3.1 Enter \Tool\WIN\afuwin32 and execute f_GtoT.bat for Windows 32bit.
 - 3.2 Enter \Tool\WIN\afuwin64 and execute f_GtoT.bat for Windows 64bit.
4. For AMD EPYC 9005 series CPU:
 - 4.1 Enter \Tool\WIN\afuwin32 and execute f.bat for Windows 32bit.
 - 4.2 Enter \Tool\WIN\afuwin64 and execute f.bat for Windows 64bit.
5. After bios flash finish, system must Power-Off to have the changes take effect.

BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press during POST
2. The bios version shows on the first main page

Known Issues/Workarounds

Issues fixed in this version

R12

- 1.[Fix] Fix PCIE compatibility when install GPU card.

R11

1. [Fix] Fix SATA information abnormal in BIOS Setup Page.

R10

BIOS Release Notes

1. [Fix] Fix OCP2 PCIe Link Speed item abnormal in BIOS Setup Page.

R09

- 1.[Feature] Update Genoa BIOS.

R08

- 1.[Feature] Adjust the DDR default max speed based on multiple models.

R07

1. [Fix] SCE tool import/export issue.
2. [Fix] Fix Redfish sends data twice after the system has completed booting.
3. [Feature] Adjust the maximum speed limit during automatic memory training.
4. [Feature] Add support for PCIe Re-Sizeable BAR functionality.

R06

- 1.[Feature] Update AGESA 1.0.0.3.
- 2.[Feature] Support DDR speed up to 6400, but it requires manual adjustment in the BIOS settings.
UMC Common Options => Enforce POR => Accept => Memory Target Speed set [DDR6400]
- 3.[Fix] Fix the issue where NVMe speed is reduced to Gen4 after a hot plug.
- 4.[Fix] Fix the issue where SEL reports incorrect DDR channel information when associated with CPU1.
- 5.[Fix] Fix the issue where the system ready to boot process gets stuck when the BMC is unresponsive.

R05

- 1.[Feature] Update AGESA 1.0.0.2.
- 2.[Fix] Fix the network configuration switching issue in the BIOS Server Manager setup.
- 3.[Fix] Fix the issue where having too many installed devices causes the system to hang at the BIOS logo screen.
- 4.[Security] CVE-2024-0179, CVE-2024-21925, CVE-2024-21944, CVE-2020-10255.
5. [Update] Added R283-Z98-AAL1-000 system support.
6. [Update] Update Inventory v19.

R04

1. [Feature] Support GBTGSI system.

R03

BIOS Release Notes

1. [Fixed] Fixed the energy optimization efficiency issue.

R02

1. [Feature] Update AGESA 1.0.0.0.
2. [Patch] AGESA 1.0.0.0 Patch3

R01

1. First release.
-