

# BIOS Release Notes

## TITLE

**SUBJECT:** MZB3-G43 BIOS Release Notes version R06\_F16

**System:** G593-ZX1-AAX1-000,G593-ZX1-LAX1-000

### About This Release

**Build Date:** 2025/03/31

**BIOS Checksum:** 0x765BE6F7 (32M)

**Release Owner:** Neil.Lu

### BIOS Components/Contents

**Processor stepping(s) supported:** AMD Turin / Genoa Processors

**System hardware configurations supported:** MZB3-G43-000

**PCB Version:** 1.x,3.x

**Microcode updates versions:**

CPUID	Family	Microcode Update ID
Turin A0	Family 1Ah Model 00h-0Fh	0x0B00004D
Turin B0	Family 1Ah Model 00h-0Fh	0x0B001016
Turin C0	Family 1Ah Model 00h-0Fh	0x0B002032
Turin C1	Family 1Ah Model 00h-0Fh	0x0B00211E
Turin Dense A0	Family 1Ah Model 00h-0Fh	0x0B10000F
Turin Dense B0	Family 1Ah Model 00h-0Fh	0x0B101028

**IPMI support:**

**AMI Kernel version:** 5.35\_0ACST\_PI1.0.0.3\_017

**AGESA PI version:** TurinPI 1.0.0.3

**OPROM version:**

OPROM	Version
AST2600	1.13.00

### Installation Notes

**IMPORTANT NOTES:**

1. Please extract the MZB3-G43\_R06\_F16.zip to a bootable diskette that use FAT/FAT32 format

**BIOS UPDATE INSTRUCTIONS FOR EFI Shell:**

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.

## BIOS Release Notes

3. Enter your USB filesystem, like "fs0:" or "fsX:", "X" is your USB filesystem number
4. Flash script for bios update:
  - 4.1 For AMD EPYC 9004 series CPU, execute f\_GtoT.nsh
  - 4.2 For AMD EPYC 9005 series CPU, execute f.nsh
5. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. For AMD EPYC 9004 series CPU:
  - 3.1 Enter \Tool\WIN\afuwin32 and execute f\_GtoT.bat for Windows 32bit.
  - 3.2 Enter \Tool\WIN\afuwin64 and execute f\_GtoT.bat for Windows 64bit.
4. For AMD EPYC 9005 series CPU:
  - 4.1 Enter \Tool\WIN\afuwin32 and execute f.bat for Windows 32bit.
  - 4.2 Enter \Tool\WIN\afuwin64 and execute f.bat for Windows 64bit.
5. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

## Known Issues/Workarounds

## Issues fixed in this version