

# BIOS Release Notes

## TITLE

**SUBJECT:** MZB3-PE0 BIOS Release Notes version R03\_F02  
**System:** G4L3-ZX1-LAX1-000,G4L3-ZX1-LAX2-000,G4L3-ZX1-LAX2-AM0,  
G893-ZX1-AAX1-000,G893-ZX1-AAX2-000,G893-ZX1-AAX2-AM0

### About This Release

**Build Date:** 2025/03/21  
**BIOS Checksum:** 0x76D392C0 (32M)  
**Release Owner:** Neil.Lu

### BIOS Components/Contents

**Processor stepping(s) supported:** AMD Turin / Genoa Processors  
**System hardware configurations supported:** MZB3-PE0-000  
**PCB Version:** 3.x  
**Microcode updates versions:**

| CPUID          | Family                   | Microcode Update ID |
|----------------|--------------------------|---------------------|
| Turin A0       | Family 1Ah Model 00h-0Fh | 0x0B00004D          |
| Turin B0       | Family 1Ah Model 00h-0Fh | 0x0B001016          |
| Turin C0       | Family 1Ah Model 00h-0Fh | 0x0B002032          |
| Turin C1       | Family 1Ah Model 00h-0Fh | 0x0B00211E          |
| Turin Dense A0 | Family 1Ah Model 00h-0Fh | 0x0B10000F          |
| Turin Dense B0 | Family 1Ah Model 00h-0Fh | 0x0B101028          |

**IPMI support:**  
**AMI Kernel version:** 5.35\_0ACST\_PI1.0.0.3\_017  
**AGESA PI version:** TurinPI 1.0.0.3  
**OPROM version:**

| OPROM   | Version |
|---------|---------|
| AST2600 | 1.13.00 |

### Installation Notes

#### IMPORTANT NOTES:

1. Please extract the MZB3-PE0\_R03\_F02.zip to a bootable diskette that use FAT/FAT32 format

#### BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.

## BIOS Release Notes

2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Flash script for bios update:
  - 4.1 For AMD EPYC 9004 series CPU, execute f\_GtoT.nsh
  - 4.2 For AMD EPYC 9005 series CPU, execute f.nsh
5. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. For AMD EPYC 9004 series CPU:
  - 3.1 Enter \Tool\WIN\afuwin32 and execute f\_GtoT.bat for Windows 32bit.
  - 3.2 Enter \Tool\WIN\afuwin64 and execute f\_GtoT.bat for Windows 64bit.
4. For AMD EPYC 9005 series CPU:
  - 4.1 Enter \Tool\WIN\afuwin32 and execute f.bat for Windows 32bit.
  - 4.2 Enter \Tool\WIN\afuwin64 and execute f.bat for Windows 64bit.
5. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

## Known Issues/Workarounds

### Issues fixed in this version

R03

1. [Feature] Support G4L3-ZX1-LAX2-AM0 and G893-ZX1-AAX2-AM0 system.
2. [Feature] Update Mapping v14 for G4L3-ZX1-LAX2-AM0 and G893-ZX1-AAX2-AM0.

R02

- 1.[Feature] Update AGESA 1.0.0.3.
- 2.[Feature] Support DDR speed up to 6400, but it requires manual adjustment in the BIOS settings.  
UMC Common Options => Enforce POR => Accept => Memory Target Speed set [DDR6400]

R01

1. PVT First release G4L3-ZX1.

## BIOS Release Notes

---