


How to update Sabre Series EC Guide

Attention : Power cord must be connected to perform before update .


注意：必須接上電源線才能執行更新動作

1. Format your USB to FAT32 (default) format .
將隨身碟格式化為 FAT32(預設)。




2. Copy EC Update file to formatted USB Disk.

將 EC 更新檔移至已格式化的隨身碟。.




3. Press power button and press F2 under the POST screen to BIOS Setup.

按下電源鍵開機並在 POST 畫面按 F2 鍵進入 BIOS Setup Utility.




Setup Secure Boot option be Disabled and Press Enter.

到Security 選項中的 Secure Boot 選擇 Disabled 按 Enter。




Press Save Changes and Reset option to reboot.

再到 Exit 選項中的 Save Changes and Reset 選擇 Yes 按 Enter 會執行重新開機。



4. In Post screen, insert the EC update USB disk and press F12 to select USB disk boot up.

重新開機後，插入隨身碟按下 F12，選擇隨身碟開機。



5. Select your USB disk amount folder (folder type is Removable Hard Disk as Red marker) ,


請選擇您的隨身碟位置 (類型為 Removable Hard Disk 如紅色框標記處) ,

- A. Input USB disk amount folder code first . (Example "fs5:" setting as below picture.)

輸入對應隨身碟編號 (例 fs5: 如下圖)

- B. Input command "ec" under USB disk amount folder.

於目標隨身碟下輸入更新指令如下ec



6. Automatically shut down after update completed .

更新完成後會自動關機。

```

EC Flash Utility for UEFI Ver 1.15.06.09      Start time 00:07:36
M/B  EC Project:  N85HJ
M/B  EC Version:  1.05.13
File EC Project:  N85HJ
File EC Version:  1.05.13
File EC Build Date:  2017/10/16      Check Sum:  47E5
Entry Flash .....      AutoLoad Disabled
Get Flash Part ID=====>      0xEF 0xEF 0xEF      Rom Size(128)K
Erase =====>
Erasing:***** Fine
Blank Check =====>
Block0: ***** Fine
Block1: ***** Fine
Blank Check success
Update data =====>
Block0: ***** Fine
Block1: ***** Fine
write success
Verify Check =====>
Block0: ***** Fine
Block1: ***** Fine
Verified success

Down count to shutdown, Waitting (0) second(s) .....
    
```

7. Restore BIOS default value to system boot up .

進入bios裡的Exit 選項中點選Restore WIN10 Defaults後按Yes。

