

BIOS Release Notes

TITLE

SUBJECT: 7PPSH BIOS Release Notes version [R20](#)

About This Release

Build Date: [2018/6/27](#)

BIOS Checksum: [0x26A3E88D](#) (4M), [0x506E6D22](#) (8M)

Release Owner: Richard Huang

BIOS Components/Contents

Processor stepping(s) supported: supports Intel® SandyBridge-EP processors

System hardware configurations supported: GA-7PPSH-RH Rev: [0.1/0.2/1.0](#)

Microcode updates versions:

CPUID	Family	Microcode Update ID
206D5	SandyBridge-EP Processor C-0	00000513
206D6	SandyBridge-EP Processor C-1 and M-0	0000061D
206D7	SandyBridge-EN -EP Processor C-2 and M-1	00000714
306E2	Ivy Bridge-EP -EX -EN Processor B-1, B-2, L-1, L-2, R-0, and R-1	0000020D
306E3	Ivy Bridge-EP -EX Processor B-3	00000308
306E4	Ivy Bridge -EX -EP -EN Processor C-0, C-1, S-0, S-1, M-0, M-1	0000042D
306E6	Ivy Bridge -EX Processor D-0	00000600

IPMI support:

AMI Kernel version: [Gbt_Kernel_F03f_15](#)

Intel CSI/MRC Package version: [02.00.00.02](#)

SPI Descriptor version: [02.01.07.129.2_BXCX_PBGHC_NM_V02](#)

OPROM version :

OPROM	Version
ASPEED VGA	0.97
Intel i350	1.3.76
Intel x540	2.1.96
LSI 2008	07.23.01.00

Installation Notes

IMPORTANT NOTES:

1. Please extract the 7PPSH_[R20](#).zip to a bootable diskette that can boot to real DOS

BIOS Release Notes

2. Please don't load HIMEM.SYS or any other memory management SW in the diskette

BIOS UPDATE INSTRUCTIONS FOR DOS:

1. Insert USB flash drive to system for BIOS upgrade
2. Power on system and boot to USB flash
3. Execute FB.BAT for bios update
 - a. Execute "FB.BAT 3" only Flash BIOS Command line
 - b. Execute "FB.BAT 2" need move ME flash jump(AC off) to flash ME firmware
4. After bios flash finish, system will reboot automatically, please do not remove USB flash
5. System will restore DMI data after boot to DOS again, please wait the message below,
"All BIOS flash steps are done! Please AC OFF and AC ON again. Thanks!"
6. Done

BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell
3. Execute \Tool\Win32\f.cmd or \Tool\Win64\f.cmd for bios update
4. After bios flash finish, Please reboot windows system

BIOS UPDATE INSTRUCTIONS FOR LINUX:

1. Insert bios update USB flash drive.
2. Use Command Shell
3. Execute \Tool\LNx\afulnx32\f.sh or \Tool\LNx\afulnx64\f.sh for bios update
4. After bios flash finish, Please reboot windows system

BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press F2 during POST
2. The bios version shows on the first main page

Known Issues/Workarounds

Issues fixed in this version

R20

1. Update microcode for Speculative Execution and Indirect Branch Prediction Side Channel Analysis Method.

R18

1. Update microcode for Speculative Execution and Indirect Branch Prediction Side Channel Analysis Method.

R16

1. Fine tune LAN setting.

R15

1. Improve BMC LAN Configuration procedure.

R13

BIOS Release Notes

1. Fix Power Capping SMI cause UEFI OS hang up.

R12

- 1.Fixed ACback function.
- 2.Add auto RBU function.

R11

- 1.Fixed used 1.35v dimm, BIOS will send 1.5v to BMC.
- 2.Fixed PEI debug mode cannot use.

R10

- 1.Fixed used Sandy CPU run DC on off stress will hang on 0xb0.

R09

1. Fixed PVDDQ voltage detection issue.

R08

1. Set Enforce DIMM to Enforce EN.
2. Disable ECC Support item for temporarily fix two E5-2650 CPU hang up at 0xB0.

R07

- 1.The IPMI SOL function fail.
- 2.one of system fail on multi bit error test.
- 3.UEFI BIOS Utility "ACPI XSDT Address Dump" and "ACPI RSDT Address Dump" show fail.
- 4.BIOS COM Port Can't Enable.
- 5.Hide SAS item.(Only for 7PTSV/7PTSH)
- 6.Fixed Fan speed control board display.

R06

1. Add iPXE and PXE OPRM shadow select item.
2. Fixed AC Lose function fail.
3. Fixed Post screen product name error.
4. Fixed SCU HDD can't be detect.
5. Add LSI onboard Raid disable item.
6. Add PIC F/W version display.

R05

1. Fixed IOH PCI root port 0,3,0 routing fail.
2. SMBIOS type1 information of "Family" is not correct.
3. Set dual SNB CPU sometimes can't power on.

R04

1. Add BMC MAC display function.
2. Adjust Lan2 OPRM default to enabled.
3. Fixed When first boot, used bad memory will occur system reboot.

BIOS Release Notes

R03

1. Fixed IVY BIOS can't let RMC get BMC/LAN1/LAN2 MAC.
2. Fixed There are some nodes do reset loop when update R02 from F11.
3. Fixed When ECC has been trigger, BIOS will disable incorrect the wrong channel.

R02

1. Fixed when set Onboard LAN Controller Disable, Device management still show LAN device.
2. Fixed when execute reboot, system will not response.
3. Fixed onboard intel SW raid on system reboot issue

R01

1. Update to IVY Bridge code base.
2. Add RBU function.
3. Fixed AC Back: Power on, Last status function test fail.
4. Add Lan MAC display function in setup menu.