

# BIOS Release Notes

## TITLE

**SUBJECT:** MZE2-G10 BIOS Release Notes version R08\_F00  
**System:** MZE2-G10-00,MZE2-G10-EV,E152-ZE0-00,E152-ZE1-00,E152-ZE1-EV

### About This Release

**Build Date:** 2024/05/29  
**BIOS Checksum:** 0x9D6B96A2 (32M)  
**Release Owner:** Auto.Build(Justin.Wu)

### BIOS Components/Contents

**Processor stepping(s) supported:** AMD Rome Processors  
**System hardware configurations supported:** MZE2-G10-00  
**PCB Version:** 1.x  
**Microcode updates versions:**

CPUID	Family	Microcode Update ID
Rome A0	Family 17h Model 30-3Fh	08300027
Rome B0	Family 17h Model 30-3Fh	0830107B

**IPMI support:**  
**AMI Kernel version:** 5.14\_RomeCrb\_0ACMK029  
**AGESA PI version:** RomePI 1.0.0.H  
**OPROM version:**

OPROM	Version
AST2600	1.11.03

### Installation Notes

#### IMPORTANT NOTES:

1. Please extract the MZE2-G10\_R08\_F00.zip to a bootable diskette that use FAT/FAT32 format

#### BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

#### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.

## BIOS Release Notes

3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.  
Or  
Enter \Tool\Win64 and execute f.bat for Windows 64bit.
4. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

### Known Issues/Workarounds

1. Windows OS does not support 256 or more logical.  
Windows 2019 can update KB44512534 to support it.

item	OS	Win2019	Win2016
IOMMU		Enable ※	Enable KB4022723
SMT Control		Enable KB4512534	Disable

※When SMT Enabled, IOMMU need to set Enabled too.

SMT Control: AMD Simultaneous Multi-Threading Technology

KB4022723: Support IOMMU on Windows 2016.

KB4512534: Support SMT on Windows 2019.

2. NVIDIA CUDA didn't support IOMMU.

### Issues fixed in this version

R08

1. Enhance Endless Retry PXE feature.

R07

1. Update AGESA 1.0.0.H.
2. Security update: CVE-2023-39538, CVE-2023-39539, CVE-2023-45229, CVE-2023-45230, CVE-2023-45231, CVE-2023-45232, CVE-2023-45233, CVE-2023-45234, CVE-2023-45235.

R06

1. Update AGESA 1.0.0.G.
2. Update Microcode 0830107A for CVE-2023-20593 issue.

# BIOS Release Notes

---

R05

1. Updated AGESA 1.0.0.E.

---

R04

1. Update AGESA 1.0.0.D.
2. Support ROT 1712.
3. Fixed USB Recovery load file issue.
4. Modify SATA Configurations Page.

---

R03

1. Fine tune flash tool for dual BIOS.
2. Support NVME LED control for system.
3. Modify BMC major number format in setup menu.

---

R02

1. Update AGESA 1.0.0.C.
2. Fixed afu check second BIOS rom failed.
3. Fixed Qlogic MAC issue in WebUI.

---

R01

1. First Release.
-