

# BIOS Release Notes

## TITLE

**SUBJECT:** MZA2-CE0 BIOS Release Notes version R14\_F01  
**System:** MZA2-CE0-00,R162-ZA0-00,R162-ZA1-00,R162-ZA2-00,R262-ZA0-00,  
R262-ZA1-00

### About This Release

**Build Date:** 2024/01/23  
**BIOS Checksum:** 0x9ED1BA1E (32M)  
**Release Owner:** Candy.Wu

### BIOS Components/Contents

**Processor stepping(s) supported:** AMD Rome Processors  
**System hardware configurations supported:** MZA2-CE0-00  
**PCB Version:** 1.x,2.x  
**Microcode updates versions:**

| CPUID   | Family                  | Microcode Update ID |
|---------|-------------------------|---------------------|
| Rome A0 | Family 17h Model 30-3Fh | 08300027            |
| Rome B0 | Family 17h Model 30-3Fh | 0830107A            |

**IPMI support:**  
**AMI Kernel version:** 5.14\_RomeCrb\_0ACMK027  
**AGESA PI version:** RomePI 1.0.0.G  
**OPROM version:**

| OPROM   | Version |
|---------|---------|
| AST2500 | 1.09.0  |

### Installation Notes

#### IMPORTANT NOTES:

1. Please extract the MZA2-CE0\_R14\_F01.zip to a bootable diskette that use FAT/FAT32 format

#### BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

#### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.

## BIOS Release Notes

2. Use Command Shell.
3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.  
Or  
Enter \Tool\Win64 and execute f.bat for Windows 64bit.
4. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

## Known Issues/Workarounds

1. Windows OS does not support 256 or more logical.  
Windows 2019 can update KB44512534 to support it.

| OS<br>item  | Win2019             | Win2016             |
|-------------|---------------------|---------------------|
| IOMMU       | Enable ※            | Enable<br>KB4022723 |
| SMT Control | Enable<br>KB4512534 | Disable             |

※When SMT Enabled, IOMMU need to set Enabled too.

SMT Control: AMD Simultaneous Multi-Threading Technology

KB4022723: Support IOMMU on Windows 2016.

KB4512534: Support SMT on Windows 2019.

2. NVIDIA CUDA didn't support IOMMU.

## Issues fixed in this version

R14

1. Support secure eraser HDD.

R13

1. Update AGESA 1.0.0.G.
2. Update Microcode 0830107A for CVE-2023-20593 issue.

R12

1. Updated AGESA 1.0.0.F.

## BIOS Release Notes

R11

1. Updated AGESA 1.0.0.E.
- 

R10

1. Update AGESA 1.0.0.D.
  2. Support ROT 1712.
  3. Modify Hotplug function for R162-ZA2.
  4. Modify SMBIOS Type 9 info.
- 

R09

1. Fine tune flash tool for dual BIOS.
  2. Support NVME LED control for system.
  3. Modify BMC major number format in setup menu.
  4. Added R162-ZA2-00 system support.
- 

R08

1. Update AGESA 1.0.0.C.
  2. Fixed afu check second BIOS rom failed.
  3. Fixed Qlogic MAC issue in WebUI.
- 

R07

1. Added Redfish - System Inventory.
  2. Fixed non-persistent boot issue.
  3. Added Setup Flash.
  4. Update SMBIOS Type130/131.
- 

R06

1. Update AGESA 1.0.0.A.
- 

R05

1. Update AGESA Label 0ACMK019.
  2. Fixed allocating tons of resource requirement when SR-IOV is enabled.
  3. Fine tune Redfish remote BIOS setup funtion.
  4. Fine tune HDD naming issue.
  5. Fine tune R162-ZA1 SATA Configuration page.
- 

R04

1. Update AGESA 1.0.0.9.
2. Fine Tune BIOS item Default string.

## BIOS Release Notes

3. Added R162-ZA1-00, R262-ZA1-00, R262-ZA2-00 system support.
4. Fixed system R162-ZA1, R262-ZA1, R262-ZA2 SATA Configuration page.
5. Changed ISL address.
6. Fine tune SLOT\_2\_Front and OCP2 Option ROM item.
7. Fine tune SLOT3 slot Auto detect issue.

---

### R03

1. Fixed when PCIE error occurs, there is no pause and warning message on the POST screen.
2. Fixed BIOS crash when used non-specification PSU device.
3. Fixed WHQL SMBIOS/USB issue.
4. Fixed RTC fail issue.
5. Fixed NVME Timeout when keep hold Ctrl + Alt + Del
6. Fixed SATA display abnormal in the middle port.
7. Adjusted Wakeup events not support with ROT systems.
8. Fine Tune BIOS item Default string.
9. Fixed NVMe Can't detect issue.
10. Added IRROM version 0005.(With ISL power 2020/10/08)

---

### R02

1. Updated AGESA 1.0.0.8.
2. Updated Redfish feature.
3. Security update for CVE-2020-10255 and CVE-2020-10713.
4. Fixed after clean CMOS system hang issue

---

### R01

1. First Release.
-