



## A M.2 SSD: How to Install the M.2 2280 SSD

M.2 SSD: Installation der M.2 2280 SSD / SSD M.2: Comment installer le SSD M.2 2280 / SSD M.2: Como instalar el SSD M.2 2280 / M.2 SSD: Como instalar o M.2 2280 SSD / SSD M.2: Come installare l'SSD M.2 2280 / M.2 SSD: Установка модуля M.2 2280 SSD / M.2 SSD: Instalacja dysku SSD M.2 2280 / M.2 SSD: M.2 2280 SSD nasıl yüklenir / M.2 SSD: M.2 2280 SSD 安裝方式 / M.2 SSD: 如何安裝 M.2 2280 SSD / M.2 SSD: M.2 2280 SSD のインストール方法 / M.2 SSD: M.2 2280 SSD 설치 방법

- Remove both the small screw secured to the M.2 SSD slot A screw hole and the pre-installed thermal plate. 取下 M.2 SSD A 插槽螺絲孔上的螺絲及預裝好的散熱片。
- Carefully insert the M.2 SSD into slot A. 小心地把 M.2 SSD 裝入 A 插槽。
- Insert the tab on the thermal plate into the slit near the connector, then secure the thermal plate and M.2 SSD in place with the previously removed screw. 把散熱片裝入插槽旁邊的缺口，然後用之前取下的螺絲將 M.2 SSD 與散熱片固定。

## B Memory Installation: SO-DIMM DDR4

Arbeitsspeicher Installation: SO-DIMM DDR4 / Installation de la mémoire: SO-DIMM DDR4 / Instalación de la memoria: SO-DIMM DDR4 / Instalação de memória: SO-DIMM DDR4 / Installazione della memoria: SO-DIMM DDR4 / Установка модулей памяти: SO-DIMM DDR4 / Instalacja pamięci: SO-DIMM DDR4 / Hafıza Yükleme: SO-DIMM DDR4 / 安裝記憶體: SO-DIMM DDR4 / 内存安装: SO-DIMM DDR4 / 메모리 설치: SO-DIMM DDR4

- Carefully insert SO-DIMM memory modules. 小心並由下層至上層安裝 SO-DIMM 記憶體於記憶體插槽。
- Push down until the modules click into place. 當記憶體固定於插槽後，再輕輕下壓至定點。
- Carefully insert SO-DIMM memory modules. 安裝下層記憶體後，重覆前述動作安裝上層記憶體。
- Push down until the modules click into place. 當記憶體固定於插槽後，再輕輕下壓至定點。

## C Wireless Module: How to Safely Remove the Module

Drahtlosmodul: Sicheres Entfernen des Moduls / Module sans fil: Comment retirer le module en toute sécurité / Módulo inalámbrico: Cómo quitar el módulo de forma segura / Módulo sem fios: Como remover com segurança o módulo / Módulo senza cavi: Come rimuovere il modulo in sicurezza / Беспроводной модуль: Безопасное отсоединение модуля / Moduł bezprzewodowy: Bezpieczne usuwanie modułu / Kablozuz Modül: Modül Güvenli Bir Şekilde nasıl Çıkarılır / 無線模組: 安全移除模組的方式 / 无线模块: 如何安全移除模块 / ワイヤレスモジュール: モジュールの安全な取り外し方法 / 무선 모듈: 모듈을 안전하게 제거하는 방법

- Disconnect the two antennas by manually lifting off the clips that hold them in place. 向上移除連接於無線模組左側頂端天線。
- Remove the screw in the middle. 鬆開固定於無線模組中央頂端的螺絲。
- Carefully pull the wireless module from the slot. 小心的把無線模組從 M.2 插槽拔除。

依據低功率電波輻射性電機管理辦法【第十二條】經型式認證合格之低功率射頻電機，非經許可公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。【第十四條】低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前項合法通信指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。」

## VESA Bracket

VESA Halterung / Support VESA / Soporte VESA / Soporte VESA / Staffa VESA / Кронштейн VESA / Wspornik VESA / VESA Braketi / VESA 支架 / VESA 支架 / VESA ブラケット / VESA 브래킷

NOTE! VESA screws: Length 5.0 mm with M3 type screws, Metal enclosure with bottom side.

- Attach the screws provided on the underside of the BRIX s Extreme. 安裝隨附的 VESA 支撐架螺絲於 BRIX s Extreme 底部。
- Attach the VESA mounting plate to the rear of a compatible display using the screws provided. 安裝隨附的 VESA 支撐架於支援 VESA 支撐架的電腦螢幕或電視機後背。
- The BRIX s Extreme can now be mounted by sliding the device into place. 將已安裝 VESA 支撐架螺絲的 BRIX s Extreme 插入 VESA 支撐架的滑軌孔，向下壓至定位點後即可固定。

## D BRIX s Extreme Support Additional SATA 6Gbps HDD: How to Install 2.5" HDD

BRIX s Extreme Unterstützt Zusätzliche SATA 6Gbps HDD: So installieren Sie die 2,5" Festplatte / Le BRIX s Extreme supporte un disque dur SATA 6Gbps additionel: Comment l'installer / Soporte adicional HDD 6Gbps SATA para BRIX s Extreme: Cómo instalar HDD 2.5" / BRIX s Extreme Soporte adicional para HDD SATA 6Gbps: Como instalar HDD 2.5" / BRIX Extreme Supporta un' ulteriore porta SATA 6Gbps per HardDisk: Come installare un HDD da 2,5" / BRIX s Extreme допускает установку дополнительного жесткого SATA-диска (6 Гбит/с): Порядок установки 2,5-дюймов жесткого диска / BRIX Extreme wspiera dodatkowy dysk SATA 6Gbps HDD: Jak zainstalować 2.5" HDD / BRIX s Extreme , extra 6Gbps HDD destekler: 2.5" HDD nasıl kurulum yapılır / BRIX s Extreme 支援額外的 SATA 6Gbps 硬碟: 如何安裝 2.5" HDD / BRIX s Extreme 支援額外的 SATA 6Gbps 硬盘: 如何安裝 2.5" HDD / BRIX s Extreme SATA 6Gbp 하드디스크(HDD) 증설: 2.5-인치 HDD의取り付け 방법 / BRIX s Extreme 는 추가 SATA 6Gbps 을 지원합니다. HDD : 2.5" HDD 를 설치하는 방법

- Unscrew and remove the HDD bracket, and then disconnect the SATA cable. 將 HDD 支架從底蓋上移除，並取下主機板上的 SATA 線。
- Screw the HDD and the bracket together with the four screws provided and connect the HDD with the SATA cable. 用隨附的四顆螺絲將 HDD 與支架鎖起來，並將 SATA Cable 與 HDD 相連。
- Install the upgrade kit board onto the bottom panel using the four screws provided, then connect the cable included in the upgrade kit to the upgrade kit board. 用隨附的四顆螺絲將升級套件固定在支架上，並將升級套件隨附的傳輸線接到升級套件上。
- Connect the other end of the cable to the SATA connector on the motherboard. 將傳輸線的另一端接到主板上的 SATA 接頭。
- Reinstall the bracket with HDD to bottom panel. 將裝有 HDD 的支架，鎖回底蓋上。

NOTE: Dual M.2 SSD Upgrade kit can be purchased additionally.

NOTE: HDD can only be installed with its thickness less than 7mm.

## D BRIX s Extreme Support LAN/COM/M.2 Upgrade Kit: How to Install LAN/COM/M.2 Kit


NOTE: This system does not support the installation of both LAN/COM kit and 2.5" HDD; also the M.2 module here cannot be equipped with a thermal plate due to the space limitation.

- Unscrew and remove the bracket, and then disconnect the SATA cable. 將支架從底蓋上移除，並取下主機板上的 SATA 線。
- Install the upgrade kit board onto the bottom panel using the four screws provided, then connect the cable included in the upgrade kit to the upgrade kit board. 用隨附的四顆螺絲將升級套件固定在支架上，並將升級套件隨附的傳輸線接到升級套件上。
- Connect the other end of the cable to the SATA connector on the motherboard. 將傳輸線的另一端接到主板上的 SATA 接頭。
- Reinstall the bracket with upgrade kit to bottom panel. 將裝有升級套件的支架，鎖回底蓋上。

## USB Power On Function: Allows Device Power-on Via USB. Useful When Mounted Behind a Display or TV

USB Power On Funktion / Fonction Démarrage par USB / Función USB Power On / Função USB Power On / Funzione USB Power On / Функция USB Power On / Опция USB Power On / USB Güç Açık Fonksiyonu / USB 埠啟動功能 / USB 接口启动功能 / USB 機器からの電源 On 機能 / USB 포트를 이용한 전원 켜기

- Press "Del" during device start up to enter BIOS. 開機後按啟 Del 鍵進入 BIOS 設定畫面。
- Select "Chipset" from the menu. 在 BIOS 主選單選擇 "Chipset"。
- Manually configure "USB S5 Wakeup Support" settings to "Enable". 進入 Chipset 的 USB S5 Wakeup Support 選項，手動控制將其 "Enable"。
- Press F4 to Save and Exit. 按啟 F4 存儲設定並離開 BIOS 選單重新開機。



NOTE: 'USB Power On' functionality in Windows requires an additional Windows patch. This is provided on GIGABYTE's official website labeled 'USB Power-On Patch'. Your GIGABYTE BRIX can be powered on via a connected USB device such as a keyboard or mouse, offering greater convenience when mounted behind a display or monitor.

注意：在 Windows 的版本環境下需要額外的應用程式來啟動 "USB Power On" 功能。你可以透過技嘉官網的產品支援與更新下載 "USB Power-On Patch" 來執行。USB Power On 提供了方便的開機功能，使用者可以透過連接到 BRIX 上的 USB 裝置啟動 BRIX；讓安裝於顯示器後方的 BRIX 更方便使用。

單元 Unit	限用物質及其化學符號 Restricted substances and its chemical symbols					
	鉛 Lead (Pb)	汞 Mercury (Hg)	鎘 Cadmium (Cd)	六價鉻 Hexavalent chromium (Cr <sup>6+</sup> )	多溴聯苯 Polybrominated biphenyls (PBB)	多溴二苯醚 Polybrominated diphenyl ethers (PBDE)
電路板總成	-	○	○	○	○	○
散熱器	○	○	○	○	○	○
外觀	-	○	○	○	○	○
電源供應器	-	○	○	○	○	○
線材	○	○	○	○	○	○

備考1. "超出0.1 wt %" 及 "超出0.01 wt %" 係指限用物質之百分比含量超出百分比含量基準值。

Note 1: "Exceeding 0.1 wt %" and "exceeding 0.01 wt %" indicate that the percentage content of the restricted substance exceeds the reference percentage value of presence condition.

備考2. "○" 係指該項限用物質之百分比含量未超出百分比含量基準值。

Note 2: "○" indicates that the percentage content of the restricted substance does not exceed the percentage of reference value of presence.

備考3. "-" 係指該項限用物質為排除項目。

Note 3: The "-" indicates that the restricted substance corresponds to the exemption.