

# BIOS Release Notes

## TITLE

**SUBJECT:** MZ92-FS2 BIOS Release Notes version R01\_F00

**System:** R282-Z97-00

### About This Release

**Build Date:** 2021/10/27

**BIOS Checksum:** 0xA48400DE(32M)

**Release Owner:** Candy.Wu

### BIOS Components/Contents

**Processor stepping(s) supported:** AMD Rome Processors

**System hardware configurations supported:** MZ92-FS2

**Microcode updates versions:**

CPUID	Family	Microcode Update ID
Rome A0	Family 17h Model 30-3Fh	08300027
Rome B0	Family 17h Model 30-3Fh	0830104D

**IPMI support:**

**AMI Kernel version:** 5.14\_RomeCrb\_0ACMK022

**AGESA PI version:** RomePI 1.0.0.C

**OPROM version:**

OPROM	Version
AST2600	1.11.03

### Installation Notes

#### IMPORTANT NOTES:

1. Please extract the MZ92-FS2\_R01\_F00.zip to a bootable diskette that use FAT/FAT32 format

#### BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

#### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.

## BIOS Release Notes

Or

Enter \Tool\Win64 and execute f.bat for Windows 64bit.

4. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

### Known Issues/Workarounds

1. Windows OS does not support 256 or more logical.  
Windows 2019 can update KB44512534 to support it.

OS item	Win2019	Win2016
IOMMU	Enable ※	Enable KB4022723
SMT Control	Enable KB4512534	Disable

※When SMT Enabled, IOMMU need to set Enabled too.

SMT Control: AMD Simultaneous Multi-Threading Technology

KB4022723: Support IOMMU on Windows 2016.

KB4512534: Support SMT on Windows 2019.

2. NVIDIA CUDA didn't support IOMMU.

### Issues fixed in this version

R01

1. First Release.
-