

BIOS Release Notes

TITLE

SUBJECT: MS33-CP0 BIOS Release Notes version [R06](#)

System: [MS33-CP0-000](#)

About This Release

Build Date: [2024/05/07](#)

BIOS Checksum: [0xA660A12C](#) (16M), [0x8E68F657](#) (64M)

Release Owner: kimberly.lin

BIOS Components/Contents

Processor stepping(s) supported: Intel® Sapphire Rapids-SP/Emerald Rapids-SP processor

System hardware configurations supported: MS33-CP0

Microcode updates versions:

CPUID	Family	Microcode Update ID
806f3	Sapphire Rapids Production D-0	0d0004b1
806f8	Sapphire Rapids All HBM Production B	2c000390
806f8	Sapphire Rapids All Production XCC E / MCC S / EE LCC U	2b0005c0
c06f2	Processor Emerald Rapids Production XCC A1 / MCC R1	21000230

IPMI support:

AMI Kernel version: [Gbt_Kernel_102_22](#)

Intel CSI/MRC Package version: [109.D34](#)

SPI Descriptor version: [06.01.04.047.0](#)

OPROM version :

BIOS Release Notes

OPROM	Version
INTEL 1G PXE	1.5.53
INTEL 1G LAN EFI	8.5.21
AST2600 VGA	1.12.00
INTEL RAID PACKAGE	RSTe 8.5.0.1096_2

Installation Notes

IMPORTANT NOTES:

1. Please extract the MS33-CP0_R06.zip to a bootable diskette that use FAT/FAT32 format

BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.
Or
Enter \Tool\Win64 and execute f.bat for Windows 64bit.
4. After bios flash finish, system must Power-Off to have the changes take effect.

BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press during POST
2. The bios version shows on the first main page

Known Issues/Workarounds

BIOS Release Notes

Issues fixed in this version

R06

1. [Feature] Support Intel TDX item.
 2. [Feature] Fine tune BMC IPv6 and IPv4 Network.
 3. [Feature] Include AMI SA50248 solution for CWE-119.
-

R05

1. [Feature] Update RC 109.D34 (EagleStream uPLR1 BKC 2024 WW12).
 2. [Feature] Update EMR Microcode : EMR Production A1/R1-Stepping:m_87_c06f2_21000230.pdb;
 3. [Feature] Update SPR Microcode : SPR Production E-Stepping:m_87_806f8_2b0005c0.pdb;SPR HBM Production B-Stepping:m_10_806f8_2c000390.pdb;
 4. [Feature] Update SPS FW to SPS_E5_06.01.04.047.0.
 5. [Feature] Update BIOS ACM / SINT to v1.1.A.
 6. [Feature] Update TDX Module to TDX_1.5.05.46.698.
 7. [Feature] Include INTEL-TA-01036 for CVE-2023-45745/CVE-2023-47855.
 8. [Feature] Include AMI SA50232 for CVE-2023-45236/CVE-2023-45237.
-

R04

1. [Bug Fix] Fix install CMT4032 can't downgrade to Gen3.
-

R03

1. [Feature] Update RC 1752.P05 (EagleStream UMR1 BKC 2024 WW05).
2. [Feature] Update EMR Microcode : No update.
3. [Feature] Update SPR Microcode : SPR Production E Stepping:m_87_806f8_2b000590.pdb;SPR HBM Production B Stepping:m_10_806f8_2c000360.pdb;
4. [Feature] Add AMI SA50218 for below CVE :
CVE-2023-45229
CVE-2023-45230
CVE-2023-45231
CVE-2023-45232
CVE-2023-45233
CVE-2023-45234
CVE-2023-45235
5. [Feature] Add AMI SA50229 for CVE-2023-3817 and CVE-2023-2650.
6. [Feature] Add AMI SA50236 for CVE-2023-5678.

BIOS Release Notes

R02

1. [Feature] Update RC 107.D52 (EagleStream PV BKC 2023 WW49).
 2. [Feature] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a1000200.pdb ; EMR Production A0-Stepping:Stepping:m_87_c06f2_21000200.pdb;
 3. [Feature] Add AMI SA50216 solution for CVE-2023-39539 and CVE-2023-39538.
-

R01

1. [Feature] Update Ami kernel 5.32_EagleStreamCrb_0ACOR_098.
 2. [Feature] Update RC 107.D20 (EagleStream BKC 2023 WW45).
 3. [Feature] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a10001d1.pdb .pdb ; EMR Production A0-Stepping:m_87_c06f2_210001B0.pdb; SPR Production E-Stepping:m_87_806f8_2b000571.pdb;SPR HBM Production B-Stepping:m_87_806f8_2c000351.pdb;
 4. [Feature] Update SPS to SPS_E5_06.01.04.005.0.
 5. [Feature] Update VROC driver to v8.5.0.1096.
-

T07

1. [Feature] Update Ami kernel 5.32_EagleStreamCrb_0ACOR_096.
 2. [Feature] Update RC 105.D74 (EagleStream BKC 2023 WW41).
 3. [Feature] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a1000190.pdb ; EMR Production A0-Stepping:m_87_c06f2_21000190.pdb; SPR Production E-Stepping:m_87_806f8_2b000541.pdb;SPR HBM Production B-Stepping:m_87_806f8_2c000321.pdb;
 4. [Feature] Update SPS to SPS_E5_06.01.04.003.0.
-

T06

1. [Feature] Base on 2023 WW37 BKC release PC version BIOS.
-

T05

1. [Bug Fix] Update Ami kernel 5.32_EagleStreamCrb_EMER_0ACOR_093.
 2. [Bug Fix] Update RC 105.D74 (EagleStream BKC 2023 WW37).
 3. [Bug Fix] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a1000161.pdb ; EMR Production A0-Stepping:m_87_c06f2_21000161.pdb;
-

T04

1. [Bug Fix] Update Ami kernel 5.32_EagleStreamCrb_EMER_0ACOR_092.
2. [Bug Fix] Update RC 105.D48 (EagleStream BKC 2023 WW35).
3. [Bug Fix] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a1000160.pdb ; EMR Production A0-Stepping:m_87_c06f2_21000160.pdb;

BIOS Release Notes

T03

1. [Bug Fix] Update Ami kernel 5.32_EagleStreamCrb_EMR_0ACOR_091.
 2. [Bug Fix] Update RC 105.D20 (EagleStream BKC 2023 WW33).
 3. [Bug Fix] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a1000150.pdb ; EMR Production A0-Stepping:m_87_c06f2_21000140.pdb;
 4. [Bug Fix] Update EMR SPS version to SPS_E5_06.01.03.011.0.
-

T02

1. [Bug Fix] Update Ami kernel 5.32_EagleStreamCrb_EMR_0ACOR_088.
 2. [Bug Fix] Update RC 103.D70 (EagleStream BKC 2023 WW27).
 3. [Bug Fix] Update EMR Microcode : EMR A0-Stepping: m_87_c06f2_a1000100.pdb ; EMR Production A0-Stepping:m_87_c06f2_210000e0.pdb;
 4. [Bug Fix] Update EMR SPS version to SPS_E5_06.01.02.048.0.
 5. [Bug Fix] Update VROC driver to v8.5.0.1042.
-

T01

1. [Feature] Update RC 102.D37 (EagleStream BKC 2023 WW21).
 2. [Feature] Update EMR Microcode : EMR A0-Stepping: EMR A0-Stepping:m_87_c06f2_a10000a0.pdb ; EMR Production A0-Stepping:m_87_c06f1_21000070.pdb;
 3. [Feature] Update EMR SPS version to SPS_E5_06.01.02.009.0.
 4. [Feature] Update VROC driver to v8.5.0.1020.
-