

# BIOS Release Notes

## TITLE

**SUBJECT:** MZ62-HD0 BIOS Release Notes version R20\_F01c  
**System:** H262-Z60-00,H262-Z61-00,H262-Z62-00,H262-Z63-00,H262-Z63-Q8,  
H262-Z66-00,H262-Z6C-NJ2

### About This Release

**Build Date:** 2021/07/09  
**BIOS Checksum:** 0xA8E0E752(32M)  
**Release Owner:** Hex.Jan

### BIOS Components/Contents

**Processor stepping(s) supported:** AMD Rome Processors  
**System hardware configurations supported:** MZ62-HD0  
**Microcode updates versions:**

CPUID	Family	Microcode Update ID
Rome A0	Family 17h Model 30-3Fh	08300027
Rome B0	Family 17h Model 30-3Fh	0830104D

**IPMI support:**  
**AMI Kernel version:** 5.14\_RomeCrb\_0ACMK020  
**AGESA PI version:** RomePI 1.0.0.A  
**OPROM version:**

OPROM	Version
AST2500	1.09.00

### Installation Notes

#### IMPORTANT NOTES:

1. Please extract the MZ62-HD0\_R20\_F01c.zip to a bootable diskette that use FAT/FAT32 format

#### BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

#### BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.

## BIOS Release Notes

3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.  
Or  
Enter \Tool\Win64 and execute f.bat for Windows 64bit.
4. After bios flash finish, system must Power-Off to have the changes take effect.

### BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

### BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press <DEL> during POST
2. The bios version shows on the first main page

### Known Issues/Workarounds

1. Windows OS does not support 256 or more logical.  
Windows 2019 can update KB44512534 to support it.

item	OS	Win2019	Win2016
IOMMU		Enable ※	Enable KB4022723
SMT Control		Enable KB4512534	Disable

※When SMT Enabled, IOMMU need to set Enabled too.

SMT Control: AMD Simultaneous Multi-Threading Technology

KB4022723: Support IOMMU on Windows 2016.

KB4512534: Support SMT on Windows 2019.

2. NVIDIA CUDA didn't support IOMMU.

### Issues fixed in this version

- 1 . Naples CPU please reference RelNotes\_Naples.PDF
- 2 . Rome CPU please reference RelNotes\_Rome.PDF