

BIOS Release Notes

TITLE

SUBJECT: MZA2-CE0 BIOS Release Notes version R04_F00a
System: R262-ZA2-00

About This Release

Build Date: 2021/01/21
BIOS Checksum: 0xA916E693(32M)
Release Owner: Candy.Wu

BIOS Components/Contents

Processor stepping(s) supported: AMD EPYC Rome Processors
System hardware configurations supported: MZA2-CE0
Microcode updates versions:

CPUID	Family	Microcode Update ID
Rome A0	Family 17h Model 30-3Fh	08300027
Rome B0	Family 17h Model 30-3Fh	0830104D

IPMI support:
AMI Kernel version: 5.14_RomeCrb_0ACMK018
AGESA PI version: RomePI 1.0.0.9
OPROM version:

OPROM	Version
AST2500	1.09.0

Installation Notes

IMPORTANT NOTES:

1. Please extract the MZA2-CE0_R04_F00a.zip to a bootable diskette that use FAT/FAT32 format

BIOS UPDATE INSTRUCTIONS FOR EFI Shell:

1. Insert USB flash drive to system for BIOS upgrade.
2. Power on system and boot to Build-In Shell.
3. Enter your USB filesystem, like "fs0:" or "fsx:", "x" is your USB filesystem number
4. Execute F.nsh for bios update
5. After bios flash finish, system must Power-Off to have the changes take effect.

BIOS UPDATE INSTRUCTIONS FOR Windows:

1. Insert bios update USB flash drive.
2. Use Command Shell.
3. Enter \Tool\Win32 and execute f.bat for Windows 32bit.

BIOS Release Notes

Or

Enter \Tool\Win64 and execute f.bat for Windows 64bit.

4. After bios flash finish, system must Power-Off to have the changes take effect.

BIOS UPDATE FOR Easy BIOS Refresh:

1. The system supports remotely update BIOS if BMC existent.
2. Please download the Easy BIOS Refresh User Guide from Gigabyte website, target system support page.

BIOS Version CHECK INSTRUCTIONS:

1. Power on system and press during POST
2. The bios version shows on the first main page

Known Issues/Workarounds

1. Windows OS does not support 256 or more logical.
Windows 2019 can update KB44512534 to support it.

OS item	Win2019	Win2016
IOMMU	Enable ※	Enable KB4022723
SMT Control	Enable KB4512534	Disable

※When SMT Enabled, IOMMU need to set Enabled too.

SMT Control: AMD Simultaneous Multi-Threading Technology

KB4022723: Support IOMMU on Windows 2016.

KB4512534: Support SMT on Windows 2019.

2. NVIDIA CUDA didn't support IOMMU.

Issues fixed in this version

R04

1. Update AGESA 1.0.0.9.
2. Fine Tune BIOS item Default string.
3. Added R162-ZA1-00, R262-ZA1-00, R262-ZA2-00 system support.
4. Fixed system R162-ZA1, R262-ZA1, R262-ZA2 SATA Configuration page.
5. Changed ISL address.
6. Fine tune SLOT 2 Front and OCP2 Option ROM item.
7. Fine tune SLOT3 slot Auto detect issue.

R03

1. Fixed when PCIE error occurs, there is no pause and warning message on the POST screen.
2. Fixed BIOS crash when used non-specification PSU device.
3. Fixed WHQL SMBIOS/USB issue.

BIOS Release Notes

4. Fixed RTC fail issue.
5. Fixed NVME Timeout when keep hold Ctrl + Alt + Del
6. Fixed SATA display abnormal in the middle port.
7. Adjusted Wakeup events not support with ROT systems.
8. Fine Tune BIOS item Default string.
9. Fixed NVMe Can't detect issue.
10. Added IRROM version 0005.(With ISL power 2020/10/08)

R02

1. Updated AGESA 1.0.0.8.
2. Updated Redfish feature.
3. Security update for CVE-2020-10255 and CVE-2020-10713.
4. Fixed after clean CMOS system hang issue

R01

1. First Release.
-