

Socket FM2+

主機板									Model	M9M3XAI
									PCB	
Vendor	CPU Model	Frequency	L2	L3	GPU	Core Name	Process	Stepping	Wattage	Since BIOS Version
			Cache	Cache	Frequency					
AMD	A10-7800	3500MHz	1MBx4	N/A	757 MHz	Kaveri	28nm	A1	65W	F1
AMD	A8-7600	3100MHz	1MBx4	N/A	757 MHz	Kaveri	28nm	A1	65W	F1
AMD	A6-7400K	3500MHz	512KBx2	N/A	800 MHz	Kaveri	28nm	A1	65W	F1
AMD	A10-6700	3700MHz	1MBx4	N/A	866 MHz	Richland	32nm	A1	65W	F1
AMD	A10-6700T	2500MHz	1MBx4	N/A	758 MHz	Richland	32nm	A1	45W	F1
AMD	A8-6500	3500MHz	1MBx4	N/A	850 MHz	Richland	32nm	A1	65W	F1
AMD	A8-6500T	2100MHz	1MBx4	N/A	758 MHz	Richland	32nm	A1	45W	F1
AMD	A6-6420K	4000MHz	512KBx2	N/A	850 MHz	Richland	32nm	A1	65W	F1
AMD	A6-6400K	3900MHz	512KBx2	N/A	850 MHz	Richland	32nm	A1	65W	F1
AMD	A4-6320	3800MHz	512KBx2	N/A	844 MHz	Richland	32nm	A1	65W	F1
AMD	A4-6300	3700MHz	512KBx2	N/A	844 MHz	Richland	32nm	A1	65W	F1
AMD	A4-4020	3000MHz	512KBx2	N/A	758 MHz	Richland	32nm	A1	65W	F1
AMD	A4-4000	3000MHz	512KBx2	N/A	758 MHz	Trinity	32nm	B0	65W	F1
AMD	A10-5700	3400MHz	1MBx4	N/A	650 MHz	Trinity	32nm	A1	65W	F1
AMD	A8-5500	3200MHz	1MBx4	N/A	650 MHz	Trinity	32nm	A1	65W	F1
AMD	A6-5400K	3600MHz	512KBx2	N/A	650 MHz	Trinity	32nm	A1	65W	F1
AMD	A4-5300	3400MHz	512KBx2	N/A	650 MHz	Trinity	32nm	A1	65W	F1
AMD	Athlon X4 750	3400MHz	1MBx4	N/A	N/A	Richland	32nm	A1	65W	F1
AMD	Athlon X4 740	3200MHz	1MBx4	N/A	N/A	Trinity	32nm	A1	65W	F1
AMD	Athlon X4 730	2800MHz	1MBx4	N/A	N/A	Trinity	32nm	A1	65W	F1
AMD	Athlon X2	4000MHz	512KBx2	N/A	N/A	Trinity	32nm	A1	65W	F1
AMD	Athlon X2 340	3200MHz	512KBx2	N/A	N/A	Trinity	32nm	A1	65W	F1