GIGABYTE

R272-Z31

Rack Server - 2U UP 24-Bay







Features

- Single AMD EPYC[™] 7002 series processor family
- 8-Channel RDIMM/LRDIMM DDR4, 16 x DIMMs
- 2 x 1Gb/s LAN ports (Intel® I350-AM2)
- 1 x Dedicated management port
- 24 x 2.5" SATA/SAS hot-swap HDD/SSD bays in front side
- 2 x 2.5" SATA/SAS hot-swap HDD/SSD bays in rear side
- Ultra-Fast M.2 with PCIe Gen3 x4 interface
- 6 x PCIe Gen4 / Gen3 expansion slots
- 1 x OCP 2.0 Gen3 x16 mezzanine slot
- Aspeed[®] AST2500 remote management controller
- 1+1 800W 80 PLUS Platinum redundant power supply


AMD EPYC[™] 7002 Series Processor (Rome)

The next generation of AMD EPYC has arrived, providing incredible compute, IO and bandwidth capability – designed to meet the huge demand for more compute in big data analytics, HPC and cloud computing.

Suilt on **7nm** advanced process technology, allowing for denser compute capabilities with lower power consumption

𝔆 Up to 64 core per CPU, built using Zen 2 high performance cores and AMD's innovative chiplet architecture

GSM Ad



Get the Memory Performance Edge

3200Mhz Even at 2 DIMMS Per Channel

On previous AMD server platforms, memory speed has been automatically downgraded by design when a user installed two DIMMs per channel. GIGABYTE has now developed a unique solution to overcome this performance downgrade headache: with our new 2nd Generation AMD EPYC 7002 Series server platforms, maximum memory speed (3200Mhz) is now supported even when using 2 DIMMS per channel*. GIGABYTE's server platforms give you the performance edge, with more memory capacity at faster speeds than competing solutions!

I AN

GIGABYTE Management Console (AMI MegaRAC SP-X)

Supporting PCIe Gen 4.0 with a bandwidth of up to 64GB/s, twice of PCIe Gen 3.0 Embedded security protection to help defend your CPU, applications, and data

This GIGABYTE server product utilizes a AMI MegaRAC SP-X platform for BMC server management, with a feature rich and easy to use browser-based graphical user interface. Notable features include:

- **RESTful API support** (including the latest DMTF standards of Redfish) allows the administrator to integrate with 3rd party applications for server management
- HTML5-based iKVM remote management client included as a standard feature, no additional add-on license required to purchase
- Detailed FRU information from SMBIOS
- · Pre-event automatic video recording feature from 10 to 30 seconds
- SAS / RAID controller monitoring feature

GIGABYTE Server Management (GSM)

GIGABYTE Server Management (GSM) is GIGABYTE's proprietary multiple server remote management software platform, available as a free download from each GIGABYTE server product page. GSM is compatible with either IPMI or Redfish (RESTful API) connection interfaces, and comprises the following sub-programs:



Specification

(WxHxD) Motherboard	2U 438 x 87.5 x 660 mm	Power Supply	1+1 800W 80 PLUS Platinum redundant PSUs
		Power Supply	AC Input: - 100-240V~/ 10-4A, 50-60Hz
	MZ32-AR0		
	AMD EPYC [™] 7002 series processor family Single processors, 7nm Up to 64-core, 128 threads per processor TDP up to 225W, cTDP up to 240W Conditional support 280W		DC Input: - 240Vdc/ 4.5A DC Output: - 800W +12V/ 66A +12Vsb/ 2.5A
	Compatible with AMD EPYC [™] 7001 series processor		NOTE:Select 1200W power supply if using 280W CPU with full loading configuration
Socket	Socet SP3	System	Aspeed® AST2500 management controller
Chipset	System on Chip	Management	GIGABYTE Management Console (AMI MegaRAC SP-X)
	16 x DIMM slots DDR4 memory supported only 8-Channel memory architecture RDIMM modules up to 64GB supported LRDIMM modules up to 128GB supported Memory speed: Up to 3200*/2933 MHz * Follow BIOS setting and memory QVL list if running 3200 Mhz with 2DPC		Dashboard JAVA Based Serial Over LAN HTML5 KVM Sensor Monitor (Voltage, RPM, Temperature, CPU Statusetc.) Sensor Reading History Data FRU Information SEL Log in Linear Storage / Circular Storage Policy Hardware Inventory Fan Profile System Firewall Power Consumption Power Constrol LDAP / AD / RADIUS Support Backup & Restore Configuration Remote BIOS/BMC/CPLD Update Event Log Filter User Management Media Redirection Settings PAM Order Settings SSL Settings SMTP Settings
	2 x 1GbE LAN ports (1 x Intel [®] I350-AM2) 1 x 10/100/1000 management LAN		
	Integrated in Aspeed [®] AST2500 2D Video Graphic Adapter with PCIe bus interface 1920x1200@60Hz 32bpp		
-	Total 26 x 2.5" SATA/SAS hot-swappable HDD/SSD bays - Front side: 24 x 2.5" SATA/SAS hot-swappable HDD/SSD bays - Rear side: 2 x 2.5" SATA/SAS hot-swappable HDD/SSD bays - All devices are connected with SAS expander Onboard SAS35x36R expander Default configuration supports: 0 x SAS/SATA drives Please select SAS card to enable the drive bays		
Expansion Slots	Total 6 x low profile PCIe Gen4 / Gen3 expansion slots - Slot_6: 1 x PCIe x16 (Gen4 x16) slot - Slot_5: 1 x PCIe x16 (Gen4 x8) slot - Slot_4: 1 x PCIe x16 (Gen4 x16) slot - Slot_3: 1 x PCIe x16 (Gen4 x16) slot - Slot_2: 1 x PCIe x16 (Gen3 x0 or x8) slot - Slot_1: 1 x PCIe x16 (Gen3 x16 or x8) slot; shared with slot_2 1 x OCP 2.0 mezzanine slot with PCIe Gen3 x16 - Type1, P1, P2, P3, P4; Type2 P5 with NCSI supported	OS Compatibility	Windows Server 2016 (X2APIC/256T not supported) Windows Server 2019 Red Hat Enterprise Linux 7.6 (x64) or later Red Hat Enterprise Linux 8.0 (x64) or later SUSE Linux Enterprise Server 12 SP4 (x64) or later SUSE Linux Enterprise Server 15 SP1 (x64) or later Ubuntu 16.04.6 LTS (x64) or later Ubuntu 18.04.3 LTS (x64) or later VMware ESXi 6.5 EP15 or later VMware ESXi 6.7 Update3 or later Citrix Hypervisor 8.1.0
	2 x M.2 slot: - M-key, PCIe Gen3 x4 - Supports NGFF-2242/2260/2280 cards	Weight	Net Weight: 16.68 kg Gross Weight: 23.66 kg
Internal I/O	2 x M.2 slots, 1 x USB 3.0 header,	System Fans	4 x 80x80x38mm (16,300rpm)
	1 x USB 2.0 header, 1 x COM_2 header, 1 x TPM header, 1 x Front panel header, 1 x HDD back plane board header, 1 x PMBus connector, 1 x IPMB connector, 1 x Clear CMOS jumper, 1 x Buzzer 1 x BIOS recovery jumper,	Operating	Operating temperature: 10°C to 35°C Operating humidity: 8%-80% (non-condensing) Non-operating temperature: -40°C to 60°C Non-operating humidity: 20%-95% (non-condensing)
Front I/O	2 x USB 3.0, 1 x Power button with LED, 1 x ID button with LED, 1 x NMI button, 1 x Reset button, 2 x LAN activity LEDs,	Packaging Content Part Numbers	1 x R272-Z31 system 1 x CPU heatsink 1 x Rail kit Barebone package: 6NR272Z31MR-00
Rear I/O Backplane I/O	1 x HDD activity LED, 1 x System status LED 3 x USB 3.0, 1 x VGA, 1 x COM, 2 x RJ45, 1 x MLAN, 1 x ID button with LED Front side_CBP2005: 24 x SATA/SAS ports		Spare parts: - Motherboard: 9MZ32AR0NR-00 - Rail kit: 25HB2-3A0202-K0R - CPU heatsink: 25ST1-15320E-J1R - SAS Expander module: 9CEP26O0NR-00 - Back plane board_12-port: 5CBP2005NR-00 - Back plane board_2-port: 9CBP2021NR-00 - Front panel board: 9CFP2001NR-00 - Fan module: 25ST2-883829-D0R - Power supply: 25EP0-208004-L0S - Fan duct for 280W CPU: 25HA8-R27231-S5R (optional)
ТРМ	Rear side_CBP2021: 2 x SATA/SAS ports Speed and bandwidth: SATA 6Gb/s or SAS 12Gb/s per port 1 x TPM header with SPI interface Optional TPM2.0 kit: CTM010		

* All specifications are subject to change without notice. Please visit our website for the latest information.

* AMD, and the AMD Arrow logo, AMD EPYC, AMD Radeon Instinct and combinations thereof are trademarks of Advanced Micro Devices, Inc.





(in) GIGABYTE