R281-3C1

Rack Server - 2U DP 12-Bay









Features

- 2nd Gen. Intel® Xeon® Scalable Processors
- 6-Channel RDIMM/LRDIMM DDR4, 24 x DIMMs
- Supports Intel[®] Optane[™] DC Persistent Memory
- Dual 1Gb/s LAN ports (Intel® I350-AM2)
- · 1 x Dedicated management port
- 12 x 3.5" and 2 x 2.5" SATAIII hot-swappable HDD/SSD bays
- Onboard 12Gb/s SAS expander
- 8 x PCIe Gen3 expansion slots
- 2 x OCP Gen3 x16 mezzanine slots
- Aspeed® AST2500 remote management controller
- Dual 1200W 80 PLUS Platinum redundant power supply

Intel® Xeon® Scalable Family Processors

GIGABYTE's Intel® Xeon® Scalable Processor family servers are available in dual socket configurations, and are compatible with the full family of different SKUs (Bronze, Silver, Gold and Platinum) that are workload optimized to support different applications, from enterprise IT database, cloud and storage to the most high-demand HPC workloads.

Compute:

- Up to 28 cores / 56 threads per socket
- Up to 38.5 MB L3 cache (non-inclusive)
- Up to 3x UPI socket interconnects @10.4 GT/s
- CPU TDP 70W 205W

I/O

• 48 PCle 3.0 lanes per socket

Memory:

- 6 channels, 2 DIMMs per channel
- Up to 12 DIMMS per socket
- Up to 2933MHz max memory speed
- Intel Optane DC Persistent Memory ready



Intel® Optane™ DC Persistent Memory Ready

GIGABYTE's 2nd Gen. Intel® Xeon® Scalable family servers come ready to support Intel Optane DC Persistent Memory, a revolutionary new product that re-defines traditional memory & storage architectures by enabling a large persistent memory tier between DRAM and SSDs, that's higher capacity than DRAM and faster than SSDs, enabling the user to bring more data closer to the CPU for faster time for insight.



GIGABYTE Management Console (AMI MegaRAC SP-X)

This GIGABYTE server product utilizes a AMI MegaRAC SP-X platform for BMC server management, with a feature rich and easy to use browser-based graphical user interface.


- RESTful API support (including the latest DMTF standards of Redfish) allows the administrator to integrate with 3rd party applications for server management
- HTML5-based iKVM remote management client included as a standard feature, no additional add-on license required to purchase
- Detailed FRU information from SMBIOS
- Pre-event automatic video recording feature from 10 to 30 seconds
- SAS / RAID controller monitoring feature

GIGABYTE Server Management (GSM)

GIGABYTE Server Management (GSM) is GIGABYTE's proprietary multiple server remote management software platform, available as a free download from each GIGABYTE server product page. GSM is compatible with either IPMI or Redfish (RESTful API) connection interfaces, and comprises the following sub-programs:

• GSM Server • GSM CLI • GSM Agent • GSM Mobile • GSM Plugin





Specification

Dimensions 2U **Power Supply** 2 x 80 PLUS Platinum 1200W redundant PSUs 438 x 87.5 x 730 (WxHxD) AC Input: - 100-240V~/ 12-7A, 50-60Hz Motherboard MR91-FS0 DC Input: - 240Vdc/ 6A CPU 2nd Generation Intel® Xeon® Scalable Processors Intel® Xeon® Platinum Processor, Intel® Xeon® Gold Processor, DC Output: Intel® Xeon® Silver Processor and Intel® Xeon® Bronze Processor - Max 1000W/ 100-240V~ CPU TDP up to 205W +12V/80.5A NOTE: If only 1 CPU is installed, some PCIe or memory functions might be unavailable +12Vsb/3A - Max 1200W/ 200-240V~ or 240Vdc input Socket 2 x LGA 3647, Socket P +12V/97A +12Vsb/3A Intel® C621 Express Chipset Chipset Aspeed® AST2500 management controller System Memory 24 x DIMM slots Management GIGABYTE Management Console (AMI MegaRAC SP-X) DDR4 memory supported only 6-channel memory per processor architecture Dashboard RDIMM modules up to 64GB supported JAVA Based Serial Over LAN HTML5 KVM LRDIMM modules up to 128GB supported Supports Intel® Optane™ DC Persistent Memory (DCPMM) Sensor Monitor (Voltage, RPM, Temperature, CPU Status ...etc.) 1.2V modules: 2933(1DPC)/2666/2400/2133 MHz Sensor Reading History Data **FRU** Information SEL Log in Linear Storage / Circular Storage Policy 1. 2933MHz for 2nd Generation Intel® Xeon® Scalable Processors only Hardware Inventory 2. Intel® Optane™ DC Persistent Memory for 2nd Generation Intel® Xeon® Scalable Processors only
3. The maximum number of DCPMM that can be installed is based on a Fan Profile System Firewall maximum operating (ambient) temperature of 35°C Power Consumption To enquire about installing a greater number of DCPMM, please consult with your GIGABYTE technical or sales representative Power Control LDAP / AD / RADIUS Support Backup & Restore Configuration Remote BIOS/BMC/CPLD Update LAN 2 x 1Gb/s BASE-T LAN ports (Intel® I350-AM2) 1 x 10/100/1000 management LAN **Event Log Filter** Video Integrated in Aspeed® AST2500 User Management 2D Video Graphic Adapter with PCIe bus interface Media Redirection Settings 1920x1200@60Hz 32bpp, DDR4 SDRAM PAM Order Settings SSL Settings Front side: 12 x 3.5" or 2.5"SATA/SAS hot-swap HDD/SSD bays Storage SMTP Settings Rear side: 2 x 2.5" SATA hot-swap HDD/SSD bays SAS card is required for SAS devices support os For Cascade Lake processors: LSI SAS35x24 expander Compatibility Windows Server 2012 R2 with Update Bandwidth: SATAIII 6Gb/s or SAS 12Gb/s per port Windows Server 2016 Default configuration supports: 2 x SATA drives Windows Server 2019 Suggested SAS cards: CRA4448, CRA4548, CRAO438, CRAO558 Red Hat Enterprise Linux 7.6 (x64) or later Red Hat Enterprise Linux 8.0 (x64) or later SATA 2 x 7-pin SATA III 6Gb/s with SATA DOM supported SUSE Linux Enterprise Server 12.3 (x64) or later By using pin_8 or external cable for power function SUSE Linux Enterprise Server 15 (x64) or later Ubuntu 18.04 LTS (x64) or later Depends on SAS add-on Card SAS VMware ESXi 6.0 Update3 or later VMware ESXi 6.5 Update2 or later RAID Depends on SAS add-on Card VMware ESXi 6.7 Update1 or later Citrix Xenserver 7.1.0 CU2 or later Riser Card CRS2131: 1 x PCle x16 slot (Gen3 x16 or x8), FHFL Expansion Citrix Xenserver 7.5.0 or later 1 x PCle x8 slots (Gen3 x0 or x8), FHFL Slots Citrix Hypervisor 8.0.0 or later 1 x PCle x8 slots (Gen3 x8), FHHL 20 kg Weight Riser Card CRS2132: 1 x PCle x16 slot (Gen3 x16 or x8), FHFL 1 x PCle x8 slots (Gen3 x0 or x8), FHFL System Fans 4 x 80x80x38mm (14'900rpm) 1 x PCle x8 slots (Gen3 x8), FHHL Operating temperature: 10°C to 35°C Operating Riser Card CRS2124: 1 x PCle x8 slots (Gen3 x0 or x8), LPHL **Properties** Operating humidity: 8%-80% (non-condensing) 1 x PCIe x16 slot (Gen3 x16 or x8), LPHL Non-operating temperature: -40°C to 60°C 2 x OCP mezzanine slots Non-operating humidity: 20%-95% (non-condensing) - PCle Gen3 x16, Type1, P1, P2, P3, P4, K2, K3 1 x R281-3C1, 2 x CPU heatsinks, 1 x Rail kit, **Packaging** Internal I/O 2 x Power supply connectors, 4 x SlimSAS connectors, 2 x SATA 7-pin Content 2 x Non-Fabric CPU carrier connectors, 2 x CPU fan headers, 1 x USB 3.0 header, 1 x TPM header, 1 x VROC connector, 1 x Front panel header, 1 x HDD back plane board header, Part Numbers Barebone package: 6NR2813C1MR-00 1 x IPMB connector, 1 x Clear CMOS jumper, 1 x BIOS recovery jumper - Motherboard: 9MR91FS0NR-00 - Rail kit: 25HB2-3A0202-K0R Front I/O 2 x USB 3.0, 1 x Power button with LED, 1 x ID button with LED, - CPU heatsink: 25ST1-353105-T1R 1 x Reset button, 1 x NMI button, 1 x System status LED, - Back plane board_12-port: 9CBP21C0NR-00 1 x HDD activity LED, 2 x LAN activity LEDs - Back plane board_2-port: 9CBP2020NR-00 - Front panel board: 9CFP2001NR-00 Rear I/O 2 x USB 3.0, 1 x VGA, 1 x COM (RJ45 type), 2 x RJ45, - Power supply: 25EP0-212002-F3S 1 x MLAN, 1 x ID button with LED - RJ45 type COM cable: 25CR0-200400-Y4R (in option) - Riser card - CRS2131: 9CRS2131NR-00 Backplane I/O Front side_CBP20C3: 12 x SATA/SAS ports - Riser card - CRS2132: 9CRS2132NR-00 Rear side_CBP2020: 2 x SATA/SAS ports - Riser card - CRS2124: 9CRS2124NR-00 Bandwidth: SATAIII 6Gb/s or SAS 12Gb/s per port - SAS cable for PCIe type SAS card: 25CFM-800821-A4R - SAS cable for OCP type SAS card: 25CFM-850820-A4R (in option) 1 x TPM header with LPC interface **TPM** - Cable for rear HDD to expander: 25CFM-05K820-A4R Optional TPM2.0 kit: CTM000

^{*} Intel, the Intel logo, the Intel Inside logo, Xeon, and Optane are trademarks of Intel Corporation or its subsidiaries.











^{*} All specifications are subject to change without notice. Please visit our website for the latest information.