



GV-RX18T512V-B

Enter the New Era of PC Gaming

Radeon X1800 SERIES X1600 SERIES X1300 SERIES

Model	GV-RX18T512V-B	GV-RX18L256V-B	GV-RX16T256V-RH	GV-RX16P256D-RH	GV-RX13P256D-RH	GV-RX13128D-RH
VPU	Radeon X1800XT	Radeon X1800XL	Radeon X1600XT	Radeon X1600Pro	Radeon X1300Pro	Radeon X1300
Core Clock	625MHz	500MHz	600MHz	500MHz	600MHz	450MHz
Mem Clock	1.5GHz	1.0GHz	1400MHz	800MHz	800MHz	800MHz
Mem Size	512MB	256MB	256MB	256MB	256MB	128MB
Mem Bus	256bit	256bit	128bit	128bit	128bit	64bit
Card Bus	PCIe X16	PCIe X16	PCIe X16	PCIe X16	PCIe X16	PCIe X16
PCB Form	ATX	ATX	ATX	ATX	ATX	ATX
Pixel Pipeline	16	16	12	12	4	4
Mem Type	DDRIII 16Mx32	DDRIII 8Mx32	DDRIII 16Mx32	DDRII 16Mx16	DDRII 16Mx16	DDRII 16Mx16
Mem Pack	uBGA	uBGA	uBGA	uBGA	uBGA	uBGA
Memory (Pcs)	8	8	4	8	8	4
Direct X	9.0C	9.0C	9.0C	9.0C	9.0C	9.0C
D-SUB	Yes(by adapter)	Yes(by adapter)	Y	Y	Y	Y
TV-OUT	S/AV	S/AV	S/AV	S/AV	S/AV	S/AV
Video-In	Y	Y	Y	N	N	N
DVI Port	2xDVH	2xDVH	DVH	DVH	DVH	DVH
MultiView	Y	Y	Y	Y	Y	Y
Fan/Heat Sink	Fansink	Fansink	SILENT PIPE II	SILENT PIPE	SILENT PIPE	SILENT PIPE
RAMDAC(MHz)	400	400	400	400	400	400
Tools	N	N	V-Tuner 2	V-Tuner 2	V-Tuner 2	V-Tuner 2

Specifications and pictures are subject to change without notice. All brand names and products are registered trademarks of their respective companies.



GV-RX55256DP

Power Your Gaming World!

Radeon X550 / X300

Model	GV-RX55256DP	GV-RX55128D	GV-RX30HM256DP	GV-R955256D	GV-R955128D	GV-R925128DE
VPU	Radeon X550	Radeon X550	Radeon X300SE +Hyper Memory	Radeon 9550	Radeon 9550	Radeon 9250
Core Clock	400MHz	400MHz	325MHz	250MHz	250MHz	240 MHz
Mem Clock	700MHz	500MHz	700MHz	400MHz	400MHz	400 MHz
Mem Size	256MB	128MB	Supporting 256MB (128MB on card)	256MB	128MB	128MB
Mem Bus	128bit	128bit	64bit	128 bit	128 bit	64 bit
Card Bus	PCIe X16	PCIe X16	PCIe X16	AGP 8X	AGP 8X	AGP 8X
PCB Form	ATX	ATX	Low Profile	ATX	ATX	Low Profile
Pixel Pipeline	4	4	4	4	4	4
Mem Type	DDRII 16Mx16	DDR 8Mx16	DDRII 16Mx16	DDR 16Mx16	DDR 8Mx16	DDR 16Mx16
Mem Pack	uBGA	TSOP	uBGA	TSOP	TSOP	TSOP
Memory (Pcs)	8	8	2	8	8	4
Direct X	9.0	9.0	9.0	9.0	9.0	8.1
D-SUB	Y	Y	Y(by adapter)	Y	Y	Y
TV-OUT	S/AV	S/AV	S/AV	S/AV	S/AV	S/AV
Video-In	N	N	N	N	N	N
DVI Port	DVH	DVH	DVH	DVH	DVH	DVH
MultiView	Y	Y	Y	Y	Y	Y
Fan/Heat Sink	Heatsink	Heatsink	Heatsink	Heatsink	Heatsink	Heatsink
RAMDAC(MHz)	400	400	400	400	400	400
Tools	V-Tuner 2	V-Tuner 2	V-Tuner 2	V-Tuner 2	V-Tuner 2	V-Tuner 2

Specifications and pictures are subject to change without notice. All brand names and products are registered trademarks of their respective companies.